

# orxCAMERA structure

## Summary

```
[CameraTemplate]
FrustumHeight = <float>
FrustumWidth  = <float>
FrustumNear   = <float>
FrustumFar    = <float>
ParentCamera  = CameraTemplate
Position      = <vector>
Rotation      = <float>
Zoom          = <float>
```

## Details

Here's a list of the available properties for an orxCAMERA structure:

- FrustumNear/FrustumFar: Defines the near and far planes for the [camera frustum](#). The near plane is excluded whereas the far plane is included when doing render culling.
- FrustumHeight/FrustumWidth: As orx's cameras are 2D ones, their frustum are [rectangle cuboids](#) instead of real [frustums](#). If you want to achieve a 1:1 aspect ratio with your main display window, you can use the `Display.ScreenHeight` and `Display.ScreenWidth` values.
- ParentCamera: If defined, this camera will be a child of the other camera in the same way it's done for orxOBJECTs that have a ParentCamera property.
- Position: Camera's initial position.
- Rotation: Camera's initial rotation (along its Z-axis).
- Zoom: Camera's initial zoom.

From:

<https://orx-project.org/wiki/> - **Orx Learning**

Permanent link:

[https://orx-project.org/wiki/en/orx/config/settings\\_structure/orxcamera?rev=1305530543](https://orx-project.org/wiki/en/orx/config/settings_structure/orxcamera?rev=1305530543)

Last update: **2025/09/30 17:26 (6 months ago)**

