orxCAMERA structure

Summary

```
[CameraTemplate]
FrustumHeight = <float>
FrustumWidth  = <float>
FrustumNear   = <float>
FrustumFar    = <float>
ParentCamera  = CameraTemplate
Position      = <vector>
Rotation      = <float>
Zoom          = <float>
```

Details

Here's a list of the available properties for an `orxCAMERA` structure:

- `FrustumNear/FrustumFar`: Defines the near and far planes for the camera frustum. The near plane is excluded whereas the far plane is included when doing render culling.
- `FrustumHeight/FrustumWidth`: As orx's cameras are 2D ones, their frustum are rectangle cuboids instead of real frustums. If you want to achieve a 1:1 aspect ratio with your main display window, you can use the `Display.ScreenHeight` and `Display.ScreenWidth` values.
- `ParentCamera`: If defined, this camera will be a child of the other camera in the same way it's done for orxOBJECTs that have a ParentCamera property.
- `Position`: Camera's initial position.
- `Rotation`: Camera's initial rotation (along its Z-axis).
- `Zoom`: Camera's initial zoom.

From:
https://orx-project.org/wiki/ - **Orx Learning**

Permanent link:
https://orx-project.org/wiki/en/orx/config/settings_structure/orxcamera?rev=1305530543

Last update: **2025/09/30 17:26 (14 months ago)**